

CREATIVE LAB

บริษัท ครีเอทีฟแล็บ เซียนใหม่ จำกัด



Sensor LC1620-PIR DC5-24V 5A

ติดต่อ : 053-235526 ,061-6545249
creativelab_cm@hotmail.co.th
Brighten up Your Business
with High Quality LED

Product introduction

- Connected to the LED Light, the light will turn on when people comes, the light will turn off when people leaves in 35 seconds.

Product Group	7
Product Name	Sensor LC1620-PIR DC5-24V 5A
Code	04-116
Model of Fitting	Aluminium outer casing
Dimension (mm) (Ø x H)	19 x 24
Input Voltage (VDC)	5-24V
Power consumption (W)	25W (5V), 60W (12V), 120W(24V)
Sensor distance	2-5 m.
Induction Angle	120 °
Delay time	35s
Installation	Flushbonading
Hole size (mm) (Ø x H)	16 x 21
Strong temperature	-20 °C ~ +60 °C
Environment temperature	-20 °C ~ +60 °C
Environmental requirement	RoHS

